


INSTRUCCIONES PANTALLA ESTANCA "LIMA".

Esta luminaria ha sido concebida tanto para uso interior como exterior.

1.- Características:

- * Grado de protección IP-66.
- * Cuerpo fabricado en ABS.
- * Difusor fabricado policarbonato.
- * Portalámparas G13.



3.- Instrucciones de instalación:

- 1.- Para proceder al montaje de la instalación, desconecte el suministro eléctrico.
- 2.- Retire el reflector girando los clips de sujeción.
- 3.- Fije las garras de ABS a los laterales del cuerpo de la luminaria.
- 4.- Desenrosque e inserte el racord en el agujero de la luminaria situado en uno de sus extremos.
- 5.- Introduzca las dos garras de fijación encontradas dentro del cuerpo de la luminaria al reflector a modo de seguridad.
- 6.- Pase los cables de alimentación a través del racord previamente instalado.
- 7.- Conecte los cables de alimentación en el bloque terminal.
- 8.- Introduzca los portalámparas G13 a cada extremo del reflector.
- 9.- Cierre el cuerpo de la luminaria con el reflector girando los clips de sujeción.
- 10.- Coloque las dos garras de acero en la parte posterior de la luminaria y fíjelo a una superficie mediante el uso de tornillos.
- 11.- Instale los tubos LED en los portalámparas G13 mediante un giro de 90º según la disposición del gráfico superior.
- 12.- Inserte el difusor al cuerpo de la luminaria y ciérrelo mediante las garras de sujeción.

4.- Instrucciones de mantenimiento:

En el caso de necesitar remplazar un tubo LED siga los siguientes pasos:

- 1.- Desconecte la red eléctrica.
- 2.- Quite el difusor de la luminaria soltando las garras.
- 3.- Deslice el tubo LED 90º que desee retirar y extráigalo.
- 4.- Instale el nuevo tubo LED en el portalámparas G13 mediante un giro de 90º según la disposición del gráfico superior.
- 5.- Inserte el difusor al cuerpo de la luminaria y ciérrelo mediante las garras de sujeción.
- 6.- Conecte la red eléctrica.

5.- Medidas de precaución:

Nota: Todos los trabajos de montaje de la luminaria, limpieza de polvo o arreglos, se deben de hacer sin conexión a la red de alimentación. Su instalación debe ser realizada por personal cualificado.

* La luminaria cumplen con las normas de seguridad CE, EN 60.598 y cumplen con la directiva RoHS sobre sustancias altamente contaminantes.


Fabricado en R.P.C.

INSTRUCTIONS SHEET FOR WATERTIGHT SCREEN LED "LIMA".

This luminaire has been designed for both indoor and outdoor use.

1.- Characteristics:

- * Protection degree IP-66.
- * Cover made of ABS.
- * Diffuser made of polycarbonate.
- * Lampholders G13.



3.- Installation instructions:

- 1.- To proceed with installation, disconnect the power supply.
- 2.- Remove the reflector spinning the holding clips.
- 3.- Attach the ABS claws to the sides of the luminaire body.
- 4.- Unscrew and insert the racord into the luminaire hole at one of its ends.
- 5.- Insert the two fixing claws found inside the luminaire body into the reflector as a safety mode.
- 6.- Pass the power cables through the previously installed racord.
- 7.- Connect the feeding wires correctly in the terminal block.
- 8.- Insert G13 lampholders at each end of the reflector.
- 9.- Close the luminaire body with the reflector spinning the fixing clips.
- 10.- Place the two steel claws on the back of the luminaire and secure it to a surface by using screws.
- 11.- Install the LED tubes in the G13 lampholders by rotating 90º according to the arrangement of the upper graphic.
- 12.- Insert the diffuser into the body of the luminaire and close it by means of the clamping claws.

4.- Maintenance instructions:

If you need to replace an LED tube, follow these steps:

- 1.- Disconnect the electric supply.
- 2.- Remove the diffuser from the luminaire by releasing the claws.
- 3.- Slide the 90º LED tube you want to remove and remove it.
- 4.- Install the new LED tube in the G13 lampholder by turning 90º according to the arrangement of the upper graphic.
- 5.- Insert the diffuser into the body of the luminaire and close it by means of the clamping claws.
- 6.- Connect the electric supply. Its installation must be carried out by qualified personnel.

5.- Caution measures:

Note: All the Works of installation, dust cleaning or arrangements must be done without the electrical supply.

* Lights fulfil the norms of security CE, EN 60.598 and they fulfil the directive RoHS about highly on highly polluting substances.

Made in P.R.C.